

MBNF-C VARIAATOR ÜHEASTMELISE REDUKTORIGA
FLANTSIGA KINNITATAV

| Korpuse mõõt | Installatsiooni mõõdud | | | | | | | | | | | | | | | | | | | | | | |
|-----------------|------------------------|---|------------|-----|-----|-----|------------|----|-----|-----|------|-----|-----|-----|----|----|-----|----|------|----|----|------|----|
| | B | C | D (js6) | F | G | H | Y (js6) | L | M | N | O | P | R | S | U | X | W | b1 | c1 | s1 | b2 | c2 | s2 |
| 0 2-C | 40 | 3 | 19 | 182 | 180 | 112 | 11 | 35 | 115 | 95 | 9 | 140 | 110 | 85 | 23 | 51 | 227 | 6 | 21,5 | M6 | 4 | 12,5 | M6 |
| 0 4-C | 50 | 4 | 24 | 211 | 188 | 131 | 14 | 39 | 130 | 110 | 10,5 | 160 | 110 | 85 | 30 | 49 | 245 | 8 | 27 | M8 | 5 | 16 | M6 |
| 0 7-C | 50 | 4 | 28 | 261 | 225 | 161 | 19 | 45 | 165 | 130 | 13 | 200 | 115 | 110 | 40 | 70 | 250 | 8 | 31 | M8 | 6 | 21,5 | M6 |

